

# Dräger X-zone® 5500

Area monitoring reinvented. That's what Dräger's X-zone® 5500 brings to a worksite: a safer, more effective way to monitor for hazardous gases. In combination with the Dräger X-am® 5000, 5100 or 5600 gas detection instruments, the X-zone® 5500 can be used for the measurement of up to six gases and extends the range of your portable gas detection technology exponentially.



#### INNOVATIVE AREA MONITORING

The Dräger X-zone 5500 transforms the Dräger X-am 5000/5100/5600 personal gas detection instruments into innovative area monitoring devices for a wide range of applications. In addition to personal air monitors carried on the body, these area monitors are positioned where gas hazards are expected to increase the level of safety.

## **CLEAR WARNING**

The illuminated green LED ring indicates that the air is free of toxic and combustible gases. Upon detection of gas hazards, the LED color changes from green to red, thus providing a clear visual warning that gas is present. Additionally, a loud and highly audible evacuation alarm is emitted. The Dräger X-zone 5500 gas entry is arranged that the gas can diffuse into Dräger X-am gas monitors from all sides.

#### **WIRELESS FENCELINE**

Up to 25 Dräger X-zone 5500 units can be automatically interconnected to form an open wireless fenceline network. A closed network may be established for up to 16 X-zone 5500 units. The interconnection allows wide safety networks in larger areas. A Dräger X-zone 5500 detecting a gas alarm transmits the alarm signal to all interconnected units. A red flashing master alarm in the mother unit detecting gas contrasts with red/green flashing alarms of the connected daughter units providing simple recognition of alarm status and the actual location of the hazard.

#### PERFECT FOR CONFINED SPACES

An integrated pump version allows for continuous monitoring of confined spaces and locations which are difficult to access, even from a distance of up to 150 ft.



Dräger X-zone® 5500 Front view



Dräger X-zone® 5500 Back view

# **DRÄGER X-ZONE 5500**

## **Front View**



## DRÄGER X-ZONE 5500

## Back view





Dräger X-zone® 5500 pictograph



## OTHER BENEFITS

360° gas entry

Daily function test and calibration not required after single on-site testing

Individually configurable with the Dräger CC-Vision PC software (e.g. alarm frequency)

Inductive charging station: easy and convenient non-contact charging

Continuous operation for up to 120 hours

## TECHNICAL DATA

Dimensions (W × H × D)	490 × 300 × 300 mm		
,	20 × 12 × 12 in.		
Weight	10 kg (22 lbs.) (24 Ah battery)		
Ambient conditions	-20 − +50 °C		
	Pressure 700 to 1,300 hPa		
	Humidity 10 to 95 % r.h.		
Ingress Protection	IP67		
Alarm	Visual 360° LED (illuminated ring)		
	Audible 360°; > 108 dB in a distance of 1 m (39 in.), 120 dB in a distance of 30 cm (1 ft.)		
	Configurable alarm patterns, frequencies and volumes		
Life signal	Green status display (360°), illuminated ring (LED)		
Operating time	Approx. 120 h (24 Ah battery)		
1 0	Depending on sensor equipment / configuration of the life signal		
Charging time	Approx. 14 h		
	Flexible power supply: External 100 – 240 V charger (worldwide) or inductive wireless charger		
Pump operation	Maximum hose length: 45 m (150 ft.)		
Alarm output	Potential-free alarm contact for intrinsically safe circuits (6-pole); < 20 V to 0.25 A (0.15 A constant current);		
	Resisting load		
Radio transmission	Worldwide license-free ISM frequencies		
	Digital radio, robust and interference-free transmission up to 100 m (328 ft.)		
RF approvals	915 MHz (USA, Canada)		
Approvals	ATEX I M1 Ex ia I Ma		
	II 1G Ex ia IIC T3 Ga		
	II 2G Ex ia d IIC T4 Gb		
	IECEx Ex ia IIC T3 Ga		
	Ex ia d IIC T4 Gb		
	Ex ia I Ma		
	CSA/US Class I, zone 0, AEx ia IIC T3 Ga		
	Class I, zone 1, AEx ia d IIC T4 Gb		

#### ORDER INFORMATION

Dräger X-zone® 5500	Part-No.
Dräger X-zone® 5500, 915 MHz, 24 Ah battery with diffusion cap	83 24 823
Dräger X-zone® 5500 with integrated pump, 915 MHz,	83 24 825
24 Ah battery with diffusion and pump cap	
X-zone® 5500 bump test adapter	83 23 314
Alarm damper	83 20 110
Leg extender stand, 25 cm high (10 in.)	83 20 645
Set: cap for Dräger X-am® 5100; for X-zone® with pump	83 23 938
Electrolube, contact protectant, 2 ml	83 24 826
Set pin block	83 25 323
Charging accessories	
Inductive charger	83 22 080
Plug-in charger	83 20 749
Pump accessories	
Float probe with 5 m or 16.4 ft. FKM hose	83 18 371
Hose set (consisting of water trap, dust and water filter)	83 21 527
FKM black hose, solvent-resistant (per foot)	12 03 150
Float probe	68 02 337
Sampling hose, clear Tygon* (per foot)	45 94 707
Tubing connector, X-am® 1/2/5000 pump	45 94 588
Filter replacement, X-am® 1/2/5000 pump	45 43 759
Communication accessories	
Dräger CC-Vision	www.draeger.com
USB DIRA with USB cable	83 17 409



Leg extender stand for elevated measurements of lighter gases



Float probe with 5 m FKM hose



Hose set consisting of water trap, dust and water filter

## CORPORATE HEADQUARTERS

Drägerwerk AG & Co. KGaA Moislinger Allee 53–55 23558 Lübeck, Germany

www.draeger.com

## CANADA

Draeger Safety Canada Ltd. 2425 Skymark Avenue, Unit 1 Mississauga, Ontario, L4W 4Y6 Tel +1 905 212 6600 Toll-free +1 877 Drager 1 (+1 877 372 4371) Fax +1 877 651 0902 Toll-free Fax +1 800 329 8823

# MEXICO

Draeger Safety S.A. de C.V. German Centre Av. Santa Fe, 170 5-4-14 Col. Lomas de Santa Fe 01210 México D.F. Tel +52 442 246-1113 Fax +52 442 246-1114

Customer Service Tel 800 723 3891

#### REGION CENTRAL AND SOUTH AMERICA

Dräger Panama S. de R.L. Complejo Business Park V tower, 10th floor, Panama City Tel +507 377-9100 Fax +507 377-9130 contactcsa@draeger.com

### USA

Draeger Safety, Inc. 101 Technology Drive Pittsburgh, PA 15275 Tel +1 412 787 8383 Fax +1 412 787 2207

Customer Service Tel 800 858 1737 Fax 800 922 5519

Technical Service Tel 888 794 3806 Fax 888 794 3807

#### Manufacturer:

Dräger Safety AG & Co. KGaA Revalstraße 1 23560 Lübeck, Germany

<sup>\*</sup> Tygon is a registered trademark of Saint-Gobain Corporation.